

Plug-and-Play Backup Power

SB-P1012-26Q – Plug-in Backup Power

SB-L10V1-20Q – In-line Backup Power

ENFORCER's Plug-and-Play Backup Power units provide backup power during temporary power outages.

The **SB-P1012-26Q** Plug-in Backup Power replaces the original 12VDC power adapter for a simplified installation.

The **SB-L10V1-20Q** In-line Backup Power installs between the original power adapter and the powered device and auto-selects 5, 7.5, 9, or 12VDC.

Features:

- Real-time backup power with no break when input power is lost
- DC UPS Auto-start
- Batteries provided by GE™ (2600mAh user-replaceable Lithium Ion - SB-P1012-26Q / 2000mAh lithium polymer - SB-L10V1-20Q)
- Over-discharge, overcharge, overload, short-circuit, and surge protection on input and output
- LED indicators for power and backup operation

Additional features for SB-L10V1-20Q

- Auto-recognize voltage (5/7.5/9/12VDC) input and set corresponding output
- Additional indicator LEDs for output voltage and an audible / visible (LED) alarm warning of an overload, voltage issue, or low battery.



SB-P1012-26Q
Plug-in Backup Power



SB-L10V1-20Q
In-line Backup Power

Specifications:

Model	SB-P1012-26Q	SB-L10V1-20Q
Type	Plug-in UPS adapter	In-line UPS
Input	85~265VAC@50/60Hz	5/7.5/9/12VDC±10%
Input protection	Overload and short-circuit fuse	
Output	12VDC±5%	Auto-configure 5/7.5/9/12VDC±5%
Output power rating	10W	
Output protection	Over-discharge, overload, short-circuit protection	
Battery	Replaceable GE™ Li-Ion 18650 3.7VDC/2600mAh	GE™ Lithium Polymer 3.7VDC/2000mAh
Battery Protection	Overcharge, over-discharge, overload, short-circuit, battery polarity	Overcharge, over-discharge, overload, short-circuit
Backup time	Half Load	70 min
	Full Load	30 min
LED indicators	Power, backup	Voltage, power, alarm, backup
Output cord	5.5ft / 1.4m	12" (30.5cm)
Output plug	5.5x2.1mm	
Operating temperature	32~104°F (0~40°C)	
Operating humidity	0~95% non-condensing	
Dimensions	3 ⁷ / ₁₆ "x2 ⁷ / ₈ "x1 ⁵ / ₃₂ " (87x59.8x29mm)	3 ³ / ₈ "x2 ¹ / ₄ "x1 ²¹ / ₃₂ " (85x57x42mm)
Weight	4.3-oz (122g)	4.3-oz (121g)

LED Status Indicators:

SB-P1012-26Q

- ⚡ Power
- 🔋 Backup

SB-L10V1-20Q

- 12V 9V 7.5V 5V
○ ○ ○ ○ Voltage (Green)
- ⚡ Power (Green)
- ⚠ Alarm (Red)
- 🔋 Backup (Yellow)

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright 2014 © SECO-LARM U.S.A. Inc. All rights reserved.

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA SLI®

PI_SB-x10xx-2xQ_160203.docx