

### Electric Door Strike

**SD-995C** For metal doors, 12VDC

**SD-995C24** For metal doors, 24VDC

The **SECO-LARM** Electric Door Strike can be used to convert cylindrical lock sets into an electronic access-controlled locking system. Combine with an optional digital keypad such as the **SECO-LARM® SK-1131-SPQ** for keyless high security.

#### Features:

- Field-programmable in just seconds for fail-safe or fail-secure applications
- Can be used with virtually any cylindrical door locking system
- Use with an optional digital keypad
- Suitable for office-type applications
- Symmetrical-sized, reversible for right-hand or left-hand doors
- Shallow design for use with most metal doors
- Powered by a solenoid, not a buzzer coil
- Jaw strength – 2,000 lbs
- Stainless-steel lip (keeper) for strength and long life
- Non-polarized connection; wires can be reversed
- Tested to 1 million cycles
- Includes trim plate to hide gaps in installation
- Optional lip-extension brackets available:
  - SD-995C-LE25 – 1" Extension
  - SD-995C-LE50 – 2" Extension



#### Also Available from **SECO-LARM®**:



**SD-994C**  
**SD-994C24**  
Electric Door Strike  
for Wood Doors



**SD-996C-NUQ**  
Universal Door Strike

#### Specifications:

Model	SD-995C	SD-995C24
Operating voltage	12VDC	24VDC
Current draw	250mA	150mA
Operating temperature	14°-113° F (-10°-45° C)	
Jaw strength	2,000-lb	
Dimensions	4 <sup>7</sup> / <sub>8</sub> "x1 <sup>1</sup> / <sub>4</sub> "x1 <sup>1</sup> / <sub>4</sub> " (124x32x32 mm)	

#### **SECO-LARM® U.S.A., Inc.**

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: [www.seco-larm.com](http://www.seco-larm.com) Email: [sales@seco-larm.com](mailto:sales@seco-larm.com)



Copyright 2015 © SECO-LARM U.S.A., Inc. All rights reserved.  
All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.  
The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

**SECO-LARM® ENFORCER® CRIMEBUSTER® CBA SLI**

PISD-995C\_151006.docx