

# 1-Channel RF Transmitters & Receiver



**SK-919TD1S-UP** 1-Channel Transmitter, Coded

**SK-919TT1S-BU** 1-Channel Transmitter, Uncoded



2 1/4" x 1 1/2" x 5/8"  
(57 x 38 x 16 mm)



- Operates up to 500 feet. 315MHz.
- Over 68 billion (6.8 x 10<sup>10</sup>) possible codes.
- LED transmission indicator.
- Includes 12VDC alkaline battery.
- Compatible with all SECO-LARM receivers.
- Private label available. Contact SECO-LARM.
- FCC certified.

**SK-919TT1S-BU:** Same as SK-919TD1S-UP, but uncoded. Code by flipping trinary dip switches. Use for "block coding" of a large number of transmitters all coded the same, or for easy matching of transmitters already in use.

**SK-939TS1S-UP:** Same as SK-919TD1S-UP, but 433.92MHz. Hand-Held Transmitters: See page 9.

**SK-910R** 1-Channel Receiver (11 to 24 VAC/VDC)



3 1/4" x 3 3/8" x 1 1/8"  
(83 x 85 x 28 mm)

- Control garage doors, house lights, alarm panels, or other devices via remote.
- Compatible with all SECO-LARM transmitters (fixed-code and CODEBUMP™).
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared.
- Mode switch for easy transmitter learning.

**SK-910R-4:** Same as SK-910R, but 433.92MHz.

Specifications	SK-910R & SK-910R2 (see page 7)
Operating Distance	Up to 500 feet (open air)*
Operating Temperature	-4°~162°F (-20°~72°C)
Operating Voltage	11-24 VDC/VAC
Current Draw	8mA @ 12VDC (standby), 45mA @ 12VDC (LED flashing)
Sensitivity	-87dBm (typical)
Data Format	PWM
RF Codes	18 quintillion (SK-917T2A-U, SK-917TP4J-NU); 68 billion (SK-919TD2A-UP, SK-919TD1S-UP, SK-919TT1S-BU, SK-919TP4J-NU, SK-919TP1H-BU, SK-919TP2H-NU, SK-919TP4H-NU)
Coded Channels	One (SK-910R/SK-910R-4), Two (SK-910R2/SK-910R2-4)
Stored Transmitter Codes	15/per channel
Receiver Outputs	Form "C" dry relay contact (N.O./N.C./Com.); max. 10 Amp @ 24VDC
Receiver Output Modes	Programmable 4-sec. momentary (default), 1-sec. momentary, toggle, or validity**

\*Increase range with SECO-LARM's Extended Range Antenna. See page 7 for details.  
\*\*Validity: Receiver will output for as long as the transmitter button is pressed.

**SK-915LP**

**SK-915BA**



Leather Pouch for SK-919TD1S-UP & SK-919TT1S-BU



12VDC Battery for all transmitters except handheld