

Video Door Phone

DP-121Q B/W, Simple 4-wire Installation

The Video Door Phone displays an image of a visitor shown in real-time on the phone's monitor, while a built-in microphone and speaker on the camera unit lets users communicate with visitors. Authorized visitors can then be granted entry with the push of a single button.

Features:

- ▶ For home or business use.
- ▶ Camera has 6 LEDs for nighttime operation.
- ▶ Remotely and securely talk to visitors.
- ▶ Remotely unlock doors, gates, etc. from the monitor.
- ▶ Simple 4-wire connection.
- ▶ Easy surface-mount installation.
- ▶ Camera and monitor turn on and off with the push of a button.
- ▶ Camera and monitor turn off automatically when not in use.
- ▶ Adjustable contrast, brightness, and ringer volume.
- ▶ LED indicators for power and operation.
- ▶ Camera contains a built-in angle adjustment.

Specifications:

Camera	
Type	B/W Camera
Chip	CCD
Resolution	380 TV lines
Relay output	1 Amp@12VDC max. dry contact
Lens	3.6mm
Min. illumination	0.8 Lux
Weight	8 oz. (220g)
Dimensions	5 ¹ / ₄ " x 3 ¹⁵ / ₁₆ " x 1 ¹ / ₂ " (134 x 100 x 38 mm)
Monitor	
Display	CRT
Weight	2 lb. 8 oz. (1.1kg)
Power consumption	800mA@15~18 VDC
Power Source	15VDC +/- 15%
Dimensions	9 ⁵ / ₈ " x 7 ¹¹ / ₁₆ " x 3 ¹ / ₈ " (245 x 196 x 79 mm)



Easily connect an additional monitor and/or an additional camera
Additional Monitor: DP-121-SQ
Additional Camera: DP-121-CQ

Sample Application:

