

2-Channel RF Transmitters & Receiver

SK-919TD2A-UP – Fixed-Code RF Transmitter SK-917T2A-U – CODEBUMP™ Transmitter

- ▶ Operates up to 500 feet. 315 MHz.
- ▶ LED transmission indicator.
- ▶ Includes 12VDC alkaline battery.
- ▶ Compatible with all SECO-LARM receivers

SK-919TD2A-UP – Fixed-code transmitter, pre-programmed to one of over 68 billion possible codes.

SK-919TD2A-U -- Same as SK-919TD2A-UP, but uncoded.

SK-917T2A-U -- Similar to SK-919TD2A-UP, but with SECO-LARM's Patented CODEBUMP™ anti-codegrabbing technology, over 18 quintillion possible codes.

2 1/4" x 1 1/4" x 1/2"
(57 x 32 x 12 mm)



SK-910R2 -- Two-Channel Receiver (11 to 24 VAC/DC)

- ▶ Control garage doors, gates, house lights, alarm panels, or other devices via remote.
- ▶ Compatible with all SECO-LARM transmitters (fixed code and CODEBUMP™).
- ▶ 2 LEDs indicate RF reception, learn mode entered, transmitter learned, memory cleared.
- ▶ 2 Mode switches for easy transmitter learning.

3 1/4" x 3 3/8" x 1 1/8"
(83 x 85 x 28 mm)



*Increase range with SECO-LARM's
Extended Range Antenna (SK-91ERSD).*

SK-919TP2H-NU

Two-Button Handheld Transmitter

- ▶ Operates up to 500 feet.
- ▶ Over 68 billion (6.8 x 10¹⁰) possible codes.
- ▶ Includes two 3VDC lithium batteries.
- ▶ Visor clip and belt clip included. Belt clip holster & wall mount bracket also available (Model: SK-9HBC).
- ▶ Slim-line design.



3 1/2" x 2 3/16" x 1/2"
(89 x 56 x 12 mm)

Technical Specifications:

	SK-910R2
Operating Distance	Up to 500 feet open air)
Operating Temperature	-4°~162° F (-20°~72° C)
Current Drain	8mA at 12VDC (standby), 45mA at 12VDC (LED flashing)
Sensitivity	-87dBm (typical)
Data Format	PWM
RF Codes	68 billion
Coded Channels	Two
Stored Transmitter Codes	15 per channel
Receiver Outputs	Form "C" dry relay contact (N.O./N.C./Com; max. 10 Amp @ 24VDC)
Receiver Output Modes	Programmable 4-sec. momentary (default) 1-sec. momentary, toggle, or validity

Copyright 2009 SECO-LARM U.S.A., Inc. Allrights reserved.

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.