

1-Channel RF Transmitters & Receiver

SK-919TD1S-UP *Factory Pre-coded Transmitter*

SK-919TT1S-BU *DIP-Switch-coded Transmitter*

- ▶ Operates up to 500ft (152m), 315MHz
- ▶ LED transmission indicator
- ▶ Includes 12VDC alkaline battery
- ▶ Compatible with all 315MHz SECO-LARM receivers
- ▶ SK-919TD1S-UP: Over 68 billion possible codes
- ▶ SK-919TT1S-BU: Use for "block coding" a large number of transmitters with the same code, or for simple matching of a transmitter already in use



1 1/2" x 2 1/4" x 5/8"
(38x63x16 mm)



2 13/16" x 3 1/2" x 1/2"
(71x89x13 mm)

SK-919TP1H-BU *One-Button Handheld Transmitter*

- ▶ Operates up to 500ft (152m), 315MHz
- ▶ Over 68 billion (6.8x10¹⁰) possible codes
- ▶ Includes two 3VDC lithium batteries
- ▶ Visor clip and belt clip included. Belt-clip holster & wall-mount bracket also available (Model: SK-9HBC)
- ▶ Slimline design

5 Programmable relay output modes



3 7/16" x 3 7/16" x 1 1/8"
(87x87x28 mm)

SK-910RBQ *One-Channel Receiver*

- ▶ Five programmable relay output modes:
 - 4-Second Momentary Output
 - Validity Output
 - Toggle Output
 - 1-Second Momentary Output
 - Latch Output
- ▶ Flexible operating voltage: 11~24 VAC/VDC
- ▶ Up to 500ft (152m) range
- ▶ Controls garage doors, gates, house lights, alarm panels, or other devices via remote
- ▶ Compatible with all 315MHz SECO-LARM transmitters (fixed code and CODEBUMP™)
- ▶ LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode
- ▶ One-button programming, no need to cut jumpers

Increase range with SECO-LARM's
Extended Range Antenna (SK-91ERSD)

SK-910RBQ Specifications:

Operating frequency	315MHz	
Memory capacity	15 transmitter button codes	
Operating voltage	11~24 VAC/VDC	
Operating current	Standby	8mA@12VDC
	Active	30mA@12VDC
Relay output modes	4-sec. momentary, toggle, latch, validity, 1-sec. momentary	
Relay contact rating	Form C 10A@24VDC/120VAC	
Connectors	Screw terminals: Power (+,-) 1 relay (NO/NC/COM)	
Dimensions	3 7/16" x 3 7/16" x 1 1/8" (87x87x28 mm)	

SECO-LARM

16842 Millikan Avenue
Irvine, CA 92606

Tel: 1-949-261-2999

1-800-662-0800

Fax: 1-949-261-7326

Web: www.seco-larm.com

Email: info@seco-larm.com



Copyright © 2011
SECO-LARM U.S.A., Inc.
All rights reserved