

ENFORCER® Sensor

SLI® 259A Dual-Stage Microwave Sensor


The SLI 259A detects the movement of mass through a protected area (i.e. an arm reaching into a car or a door being opened). The SLI 259A has dual-zone protection. It combines both perimeter pre-intrusion warning and instant interior trigger protection. It does this by transmitting and receiving a high-frequency RF signal. When an object moving towards the vehicle is detected, the high-frequency RF signal will change. This change will cause the microwave sensor to send a trigger signal to the alarm.

Features

- ▶ Ideal for vehicles with cloth or open tops, or open sunroofs.
- ▶ Dual-stage protection — Chirps siren if exterior zone violated (someone gets too close to car), triggers alarm if interior zone is violated (break-in or vandalism attempt).
- ▶ Plugs directly into any ENFORCER alarm. Easily connects to non-ENFORCER alarms.
- ▶ Separate microfine sensitivity adjustment of interior and exterior zones for excellent zone separation.
- ▶ Built-in LED indicates interior and exterior zone status.



Example of installing the SLI 259A with an ENFORCER® Alarm and SS-052B Shock Sensor (No SR-199-315 Y-connector, splicing instead)



SLI 259A Specifications

No. of zones	2
Trigger output	Transistor ground
Pre-alert output	Transistor ground
LED	Tri-color
LED status indication	Power-up, incorrectly connected, sensitivity, internal and external zone trigger status
No. of sensitivity adjustment pods	2
Programmable external protection?	Triggers the alarm if 4 pre-intrusion alerts occur within 15 sec.

Save time and money!

The SR-199-315 Y-connector allows the SLI 259A microwave sensor and the SS-052B shock sensor to be installed on any ENFORCER alarm in seconds. *No splicing needed!*



The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® U.S.A., Inc., 16842 Millikan Avenue, Irvine, CA 92606 Tel: 1-800-662-0800 (Domestic U.S. & Canada)
Tel: 1-949-261-2999 (California & International) Fax: 1-949-261-7326 Email: info@seco-larm.com Website: www.seco-larm.com

SLI259.pmd