

FOR IMMEDIATE RELEASE
SECO-LARM® SALES DEPARTMENT
(800) 662-0800
(949) 261-2999
Fax: (949) 261-7326
e-mail: info@seco-larm.com
website: www.seco-larm.com



SECO-LARM Introduces the New SK-910R4 4-CHANNEL RECEIVER

SECO-LARM introduces its hot new four-channel RF receiver with four independently programmable outputs. The SK-910R4 is a full-featured four-channel receiver with four built-in Form-C dry (N.O./N.C./Common) relay outputs with a maximum current rating of 10 Amps at 24VDC.

The SK-910R4 requires a working voltage of 11~24VDC/VAC for a wide range of applications.

Use the SK-910R4 four-channel receiver in place of keypads and key locks for wireless RF remote control of alarm control panels, garage doors, house lights or other devices from up to 500 feet away with the incorporated antenna. However, the SK-910R4 also features easy plug-in of SECO-LARM's extended range antenna (Model # SK-91ERSD), to increase the range up to as much as 1200 feet.

The SK-910R4 features Hi-Q selectivity and a coding IC for rejecting unwanted RF signals, higher sensitivity, unsurpassed antenna matching capabilities and greater tuning stability.

The four outputs are independently programmable: timed momentary (1,2,3,4,5,10,30,60 sec.), toggle (ON/OFF), latched, and continuous, plus there are four LEDs, one per channel, to indicate RF reception, learn mode, transmitter cleared, output type.

The SK-910R4 is capable of learning up to 15 different transmitter codes per channel, and can use all SECO-LARM transmitters, including the 4-button SK-917T4J (code-hopping) and SK-919T4J (fixed-code).



The **SK-910R4** is just one of **SECO-LARM's** wide selection of alarms and accessories for the security and electronics industries. For more information about the **SK-910R4** or any of **SECO-LARM's** full line of residential and commercial security systems and accessories, or to request our latest catalog, please contact the **SECO-LARM** Sales Department (949) 261-2999 (California), fax (949) 261-7326 or (800) 662-0800, or visit us on the Web at **seco-larm.com**.