# Reversible Electric Door Strikes

## **SD-994A-A1AQ**

Asymmetric – the strike portion is not centered on the reversible faceplate SD-994A-A1SQ

Symmetric – the strike portion is centered on the reversible faceplate

#### **Features:**

- 8~16 VAC/12VDC Operating voltage
- For use on wood doors
- Can be used with virtually any cylindrical-door locking system
- Fail-secure operation
- US26D Chrome faceplate
- Miniature lock body for easier installation
- Faceplate size:  $5^{7}/8^{n}x_{1}^{1}/4^{n}x_{1}^{1}/8^{n}$  (150x32x3.2 mm)
- Corrosion-resistant case and moving parts
- 1,000-lb (453kg) Jaw strength
- Tested to 500,000 cycles
- Reversible for right- or left-hand doors
- Current draw: 800mA@16VAC

750mA@12VDC

- Keeper depth: 21/32" (16.8mm)
- Latch depth: 3/4" (19mm)

## Strike depth: $1^{1}/_{2}^{"}$ (38mm) **Dimensions: Specifications:**

	SD-994A-A1AQ / SD-994A-A1SQ
	Fail secure
	8~16 VAC/12VDC
16VAC	800mA
12VDC	750mA
ure	14°~113° F (-10°~45° C)
	10.3-oz (292g)
	12VDC



#### SD-994A-A1AQ SD-994A-A1SQ 13/16" (32mm) 13/16" (20mm) (58mm) (34mm) (150mm) $(150 \text{mm})_{15/1}$ (75mm) 31/8" Ø (80mm) 1<sup>3</sup>/<sub>8</sub>" 53/8" € (34mm) (58mm) 136mm 1<sup>3</sup>/<sub>8</sub>" (34mm)

### SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com





