

# **Infrared Proximity Sensors**

**CS-PD535-TAQ** Square, Red/Green LED status indicator **CS-PD535-TBQ** Square, Blue/Green LED status indicator

### Features:


- No-touch operation reduces the risk of spread of germs, viruses, etc., through cross-contamination
- Adjustable sensor range 2<sup>3</sup>/<sub>8</sub>"-8" (6~20 cm), 3A relay, adjustable trigger duration 0.5~30 seconds or toggle
- LED illuminated sensor area for easy identification
- Selectable LED colors turns from red to green or green to red (blue to green / green to blue for CS-PD535-TBQ) to show the sensor is activated

### **Specifications:**


Model		CS-PD535-TAQ	CS-PD535-TBQ
Operating voltage		12~24 VDC	
Current draw (max.)		120mA@12VDC	
Relay type		Form C dry contact, NO/NC/COM, 3A@24VDC	
Connectors		Quick-connect, screwless terminal block	
Response time		10mS	
Output time		Adjustable, 0.5~30s, toggle, or as long as sensor is triggered	
Sensing range		Adjustable, 23/8"~8" (6~20cm)	
LED Status indicator		Red/green or green/red*	Blue/green or green/blue*
Operating life	Relay	500,000 cycles	
	Sensor	100,000 hours	
Case material		ABS Plastic	
Operating temperature		-4°~131° F (-20°~55° C)	
Dimensions		1 <sup>3</sup> / <sub>4</sub> "x2 <sup>1</sup> / <sub>8</sub> "x1 <sup>7</sup> / <sub>16</sub> " (44x55x37 mm)	

<sup>\*</sup>Colors reversable by jumper

### **Sample Applications:**




Access control



Replace mechanical switch (machinery, dispensers, medical devices, etc.)

### **Overview:**

# 13/<sub>4</sub>" (44mm) 2" (50mm) (43mm)



### **LED Indicators (Selectable):**

(CS-PD535-TAQ shown)







Activated

## SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

**Phone:** (949) 261-2999 | (800) 662-0800 **Fax:** (949) 261-7326 **Website:** www.seco-larm.com **Email:** sales@seco-larm.com





