


DVR Firmware Update

DR-1 Series H.264 DVR

2nd Generation	Firmware Release Date
	10/01/2012

1st Generation	Firmware Release Date
	10/01/2012

FAQ:

Question 1: How do I check my firmware version?

Answer:


1. Access the "System Setup" menu in the DVR menu.
 2. Select the "System/Version Info" page. Your current firmware version will be displayed.
-

Question 2: How do I upgrade my firmware via internet?

Note: Upgrading firmware via the internet is only available on 2nd generation DR-1 series DVRs. To determine if your DVR is 2nd generation, check the back panel for HDMI® output. Only 2nd generation DVRs have HDMI® output.

Answer:

1. Access the "System Setup" menu in the DVR menu.
2. Select the "System/Version Info" page. Your current firmware version will be displayed
3. Select the option "Software Upgrade via Internet"

 **NOTE:** Do NOT disconnect the power during the software update. Please ensure that the power is not disconnected until the DVR is completely rebooted. Failure to do so may damage the device.


Question 3: How do I upgrade my firmware via USB flash drive?

Answer:

1. Download the most recent firmware from the SECO-LARM website directly to your desktop.
2. Copy the folder and all its contents to a USB flash drive. Make sure the folder is directly in the root of the USB flash drive.

NOTE: Folder is named upd_88ts for 2nd generation DVRs and upd_084s for 1st generation DVRs.

3. Place the drive into the DVR's front USB port.
4. Access the "System Setup" in the DVR menu.
5. Select the "System/Version Info" page. Your current firmware version will be displayed.
6. Select the option "Software Upgrade Via Local Device."

 **NOTE: Do NOT disconnect the power during the software update.** Please ensure that the power is not disconnected until the DVR is completely rebooted. Failure to do so may damage the device.

HDMI®, the HDMI Logo and High-Definition Multimedia Interface® are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries.