

30W PoE+ Injector

NJ-A301U-T6AQ

The ENFORCER 30W PoE+ Injector converts 100~240 VAC to low voltage DC and supplies power to IP cameras, IP access control, and other PoE devices using Cat5e or Cat6 cables. This allows you to supply power to IEEE 802.3af/at compliant network accessories without an external power supply and provides a compact, reliable, and affordable solution to your networking infrastructure.

Features

- Supports up to 30W on 2-pairs
- LED indicates power supply input and PoE output
- Internal AC/DC converter
- Easy Plug-and-Play installation
- Connects to 10/100/1000BASE-T PoE devices
- Overcurrent, overload, overvoltage, and anti-interference protection
- Built-in surge protection
- Supports Cat5e network cables and higher
- Compliant with IEEE 802.3af/at standard












Specifications

Operating voltage		100~240 VAC
Connections	Data In	1x Shielded RJ45
	PoE Out	1x Shielded RJ45
PoE Power output		Up to 52VDC, 30W
Power link		Pin 1/2 (-), 3/6 (+) up to 30W
Network cables		Cat5e or higher
Protection		Overcurrent, overload, overvoltage, anti-interference
Ethernet speed		10/100/1000 Mbps
LED Indicator		Green – power in, red – power out
Operating humidity		90% (Maximum, non-condensing)
Operating temperature		14°~104° F (-10°~°40 C)
Dimensions		4 ³ / ₄ "x2"x1 ⁷ / ₁₆ " (121x50x36 mm)

Sample Application



SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606 **Phone:** (949) 261-2999 | (800) 662-0800 **Fax:** (949) 261-7326 **Website:** www.seco-larm.com **Email:** sales@seco-larm.com

€(€