

Armored Door Cords

Installation Manual

- Designed to carry wiring to conduct power to electric locks or access systems mounted in doors/gates
- Conceal unsightly wiring and protect from vandals
- Mounting screws included
- Surface-mount



SD-969-T15Q/S shown



Model	End caps	Pre-Wired Terminals	Color
SD-969-A18Q	Plastic	No	Silver
SD-969-A18/K	Plastic	No	Black
SD-969-S18Q	Aluminum	No	Silver
SD-969-S18/K	Aluminum	No	Black
SD-969-T15Q/B	Aluminum	Yes	Bronze
SD-969-T15Q/S	Aluminum	Yes	Silver
SD-969-T15Q/K	Aluminum	Yes	Black
SD-969-M15Q/B	Aluminum	No	Bronze
SD-969-M15Q/S	Aluminum	No	Silver
SD-969-M15Q/K	Aluminum	No	Black

SD-969-A18Q – Plastic End Caps

SD-969-A18Q – Silver

SD-969-A18/K – Black

- 16" (41cm) Stainless steel armored cord
- Inside door-cord diameter: $\frac{5}{16}$ " (8mm)
- Outside door-cord diameter: $\frac{7}{16}$ " (11mm)



SD-969-S18Q – Aluminum End Caps

SD-969-S18Q – Silver

SD-969-S18/K – Black

- Die-cast aluminum end caps
- 17" (43cm) Stainless steel armored cord
- Inside door-cord diameter: $\frac{5}{16}$ " (8mm)
- Outside door-cord diameter: $\frac{1}{2}$ " (13mm)



SD-969-M15Q – Aluminum End Caps

SD-969-M15Q/B – Bronze

SD-969-M15Q/S – Silver

SD-969-M15Q/K – Black

- Die-cast aluminum end caps
- Once mounted, simply remove the cover to access wiring connections
- No need to remove from the door, thus preventing stripping of screws and mounting points
- 15" (39cm) Stainless steel armored cord
- Inside door-cord diameter: $\frac{5}{16}$ " (8mm)
- Outside door-cord diameter: $\frac{7}{16}$ " (11mm)
- Security screws (included) prevent tampering



SD-969-M15Q/B shown

SD-969-T15Q – Prewired, Terminal Blocks, and Aluminum End Caps

SD-969-T15Q/B – Bronze


SD-969-T15Q/S – Silver

SD-969-T15Q/K – Black

- Includes terminal blocks with pre-wired cables (8 connections) for quick, easy, and secure installation
- Once mounted, simply remove the cover to access wiring connections
- No need to remove from the door, thus preventing stripping of screws and mounting points
- Maximum current – 3A@30VAC/VDC
- Die-cast aluminum end caps
- 15" (39cm) Stainless steel armored cord
- Inside door-cord diameter: $\frac{5}{16}$ " (8mm)
- Outside door-cord diameter: $\frac{7}{16}$ " (11mm)
- Security screws (included) prevent tampering



SD-969-T15Q/S shown



Terminal layout

IMPORTANT: Users and installers of this product are responsible for ensuring that the installation and configuration of this product complies with all national, state, and local laws and codes. SECO-LARM will not be held responsible for the use of this product in violation of any current laws or codes.

California Proposition 65 Warning: These products may contain chemicals which are known to the State of California to cause cancer and birth defects or other reproductive harm. For more information, go to www.P65Warnings.ca.gov.

WARRANTY: This SECO-LARM product is warranted against defects in material and workmanship while used in normal service for one (1) year from the date of sale to the original customer. SECO-LARM's obligation is limited to the repair or replacement of any defective part if the unit is returned, transportation prepaid, to SECO-LARM. This Warranty is void if damage is caused by or attributed to acts of God, physical or electrical misuse or abuse, neglect, repair or alteration, improper or abnormal usage, or faulty installation, or if for any other reason SECO-LARM determines that such equipment is not operating properly as a result of causes other than defects in material and workmanship. The sole obligation of SECO-LARM and the purchaser's exclusive remedy, shall be limited to the replacement or repair only, at SECO-LARM's option. In no event shall SECO-LARM be liable for any special, collateral, incidental, or consequential personal or property damage of any kind to the purchaser or anyone else.

NOTICE: The SECO-LARM policy is one of continual development and improvement. For that reason, SECO-LARM reserves the right to change specifications without notice. SECO-LARM is also not responsible for misprints. All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. Copyright © 2025 SECO-LARM U.S.A., Inc. All rights reserved.

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606
Phone: (949) 261-2999 | (800) 662-0800

Website: www.seco-larm.com
Email: sales@seco-larm.com

 PITGW1

ML_SD-969-x1xQ_250926.docx