

Armored Door Cords with Removable Covers

- SD-969-M15Q/S** *Removable Covers, Silver*
- SD-969-M15Q/B** *Removable Covers, Bronze*
- SD-969-M15Q/K** *Removable Covers, Black*
- SD-969-T15Q/S** *Pre-Wired Terminal Blocks, Silver*
- SD-969-T15Q/B** *Pre-Wired Terminal Blocks, Bronze*
- SD-969-T15Q/K** *Pre-Wired Terminal Blocks, Black*



SD-969-M15Q/S

SD-969-T15Q/S



SD-969-M15Q/B

SD-969-T15Q/B



SD-969-M15Q/K

SD-969-T15Q/K

Features

- Designed to carry wiring to conduct power to electric locks or access systems
- Once mounted, simply remove the cover to access. Door cord stays in place. No need to remove from the door. Prevents stripping of the screws and mounting points
- Surface-mounted
- Terminal blocks with pre-wired cables (8 connections) for quick, easy, and secure installation (SD-969-T15Q only)
- Maximum current – 3A@30VAC/VDC (SD-969-T15Q only)
- 15" (39cm) Stainless steel armored cord
- Inside door-cord diameter: 5/16" (8mm)
- Outside door-cord diameter: 7/16" (11mm)
- Security screws (included) prevent tampering
- Available in bronze, black, or silver finish

Specifications

Model	SD-969-M15Q	SD-969-T15Q
Cord length	15" (39cm)	
Pre-wired terminal block	No	Yes
Maximum current	N/A	3A@30VAC/VDC
Construction	Stainless steel armored	
Outside diameter	7/16" (11mm)	
Inside diameter	5/16" (8mm)	
End cap dimensions	2 3/16" x 7/8" x 1 9/16" (55x22x40 mm)	

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright © 2026 SECO-LARM U.S.A., Inc. All rights reserved.
 All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.
 The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA® SLI®

PI_SD-969-x15Qx_251226.docx

Cables para Puertas Blindadas con Cubiertas Removibles

- SD-969-M15Q/S** *Cubiertas Removibles, Plata*
- SD-969-M15Q/B** *Cubiertas Removibles, Bronce*
- SD-969-M15Q/K** *Cubiertas Removibles, Negro*
- SD-969-T15Q/S** *Bloques de Terminales Pre-Cableados, Plata*
- SD-969-T15Q/B** *Bloques de Terminales Pre-Cableados, Bronce*
- SD-969-T15Q/K** *Bloques de Terminales Pre-Cableados, Negro*

Funciones

- Diseñado para transportar el cableado que conduce energía a cerraduras eléctricas o sistemas de acceso
- Una vez instalado, simplemente retire la cubierta para acceder. El cordón de la puerta permanece en su lugar. No es necesario retirarlo de la puerta. Evita el desgaste de los tornillos y puntos de montaje
- Montaje en superficie
- Bloques de terminales con cables preinstalados (8 conexiones) para una instalación rápida, sencilla y segura (solo modelo SD-969-T15Q)
- Corriente máxima: 3A@30VCA/VCC (solo modelo SD-969-T15Q)
- Cordón blindado de acero inoxidable de 15" (39 cm)
- Diámetro interno del cordón: 5/16" (8 mm)
- Diámetro externo del cordón: 7/16" (11 mm)
- Tornillos de seguridad (incluidos) para evitar manipulaciones
- Disponible en acabado bronce, negro, o plata



SD-969-M15Q/S

SD-969-T15Q/S



SD-969-M15Q/B

SD-969-T15Q/B



SD-969-M15Q/K

SD-969-T15Q/K

Especificaciones

Modelo	SD-969-M15Q	SD-969-T15Q
Longitud del cordón	15" (39cm)	
Bloque de terminales precableado	No	Sí
Corriente máxima	N/A	3A@30VCA/VCC
Construcción	Acero inoxidable blindado	
Diámetro externo	7/16" (11mm)	
Diámetro interno	5/16" (8mm)	
Dimensiones de la tapa terminal	2 ³ / ₁₆ "x7 ⁷ / ₈ "x19 ¹ / ₁₆ " (55x22x40 mm)	

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Webseite: www.seco-larm.com Email: sales@seco-larm.com



Copyright © 2026 SECO-LARM U.S.A., Inc. Todos los derechos reservados. Todas las marcas comerciales son propiedad de SECO-LARM U.S.A., Inc. o sus respectivos propietarios. La póliza de SECO-LARM es de desarrollo y mejora continua. Por esa razón, SECO-LARM se reserva el derecho de cambiar las especificaciones y los precios sin previo aviso. SECO-LARM tampoco es responsable de errores de impresión.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA® SLI®

PI_SD-969-x15Qx_251226.docx